

Download the latest installation sheets via the official website or QR code.

07060201-0839-001  
 Date 2025-12-29  
 CN  
 EN Instruction Sheet

HCFA WW.

5

Zhejiang Hechuan Technology Co.,Ltd  
 No.5, Qinshan Road, Longyou Industrial Zone, Quzhou City, Zhejiang Province



## Safety precautions

The products in this manual are industrial products and are all open-type housing designs. It is essential to install these products within a control cabinet that is safeguarded against dust, moisture, and accidents such as electric shocks or physical impacts. Additionally, protective measures must be taken to prevent malfunctions or damage caused by improper operation or accidents involving non-maintenance personnel. Failure to do so may lead to serious risks to personnel safety and potential loss of property.

## Model identification

<u>MXB</u>		<u>BD</u>		<u>XXXX</u>																				
1	2	3	4	5	6																			
<table border="1"> <tr><td>HC</td><td>Hechuan Technology)</td></tr> <tr><td>MXB</td><td>M M-Series optional expansion</td></tr> </table>		HC	Hechuan Technology)	MXB	M M-Series optional expansion	<table border="1"> <tr><td>ID04</td><td>4 (4-channel standard input)</td></tr> <tr><td>OD04</td><td>4 (4-channel standard output)</td></tr> <tr><td>200</td><td>M200 M200 series optional card</td></tr> </table>		ID04	4 (4-channel standard input)	OD04	4 (4-channel standard output)	200	M200 M200 series optional card	<table border="1"> <tr><td>BD</td><td>BD</td><td>Optional BD card)</td></tr> <tr><td>XXXX</td><td colspan="2">0-9/A-Z/ (N/A)</td></tr> <tr><td>PNP</td><td colspan="2">Source type</td></tr> </table>		BD	BD	Optional BD card)	XXXX	0-9/A-Z/ (N/A)		PNP	Source type	
HC	Hechuan Technology)																							
MXB	M M-Series optional expansion																							
ID04	4 (4-channel standard input)																							
OD04	4 (4-channel standard output)																							
200	M200 M200 series optional card																							
BD	BD	Optional BD card)																						
XXXX	0-9/A-Z/ (N/A)																							
PNP	Source type																							

## Applicable model

Expansion Card Type	Model	Channels	Input Type	Output Type	Notes
Digital input expansion card	HCMXB-ID04-200-BD	4	NPN PNP		4-channel digital input, supports NPN and PNP
Digital output expansion card	HCMXB-OD04-200-BD	4		NPN	4-channel digital output, chip output, supports NPN
	HCMXB-OD04-200-BD-PNP	4		PNP	4-channel digital output, chip output, supports PNP

\* Note: The digital expansion card can be installed in the host expansion slot 1 or 2, with a maximum of two installable (supporting single-slot or dual-slot installation).

## General electrical and environmental specifications

HCMXB-ID04-200-BD	DC3.3V/0.1W	DC3.3V/0.1W	DC24V, 5mA/Ch	Digital input: DC24V, 5mA/Ch
HCMXB-OD04-200-BD			DC24V, 500mA/Ch, 2A/4Ch*3 / /	Digital output: DC24V, 500mA/Ch, 2A/4Ch*3 Load type: Resistive/Inductive/Lamp loads
HCMXB-OD04-200-BD-PNP			DC24V, 500mA/Ch, 2A/4Ch*3 / /	Digital output: DC24V, 500mA/Ch, 2A/4Ch*3 Load type: Resistive/Inductive/Lamp loads

\* 1. LPS SELV  
 2.  
 3.

\*Note: 1. All models can only operate under the safety extra low voltage (SELV) provided by a limited power source (LPS).  
 2. The power rating indicated here is the maximum power under full-load operation.  
 3. Consider the effect of temperature rise and derate during using.

Altitude	2000m	2000m
Operating environment	Installation within a control cabinet, open-type and indoor use	
Operating temperature	0-55	0-55
Storage temperature	-25-70	-25-70
Ambient humidity	10-95%RH	10-95%RH (non-condensing)
Vibration resistance	5-150Hz X/Y/Z	1g/3.5mm
Pollution degree	2	Level 2
Cooling method	Natural air cooling	
IP rating	IP20	
Enclosure material	Self-extinguishable	

\*Note: If the equipment is used in a manner not specified by the manufacturer, the protection provided by the equipment may be impaired.



Indicator description

[Redacted]

[Redacted]

[Redacted]

[Redacted]

[Redacted]

[Redacted]